



---

## SCHEDULE A — AVAILABLE EDTI INVESTMENT

### 1. Maximum Investment

The maximum investment that EDTI will make in new services or expansions for Residential, General Service and Industrial Customer classes is as follows:

(a) Residential Customers:

- for new (raw land) underground development areas, EDTI will provide a contribution of \$2,820 for each lot;
- for single family residential, rural acreage and farm in a previously unserved area to be serviced with overhead power, EDTI will install single-phase overhead primary lines on public roadways up to an existing lot within the boundary of the City of Edmonton at no charge and will provide a contribution of up to \$872 for the transformer installation and the Service Connection;
- for multiple family residential, in a previously serviced area, EDTI will provide a contribution of \$562 for each Service Connection.

(b) General Service and Industrial Customers

- \$290 per kVA of Contracted Minimum Demand for the Service Connection for the first 2,500 kVA and \$130 per kVA thereafter.
- for a raw land industrial subdivision adjacent to an existing subdivision with three-phase service, EDTI will extend the overhead three-phase primary service on public roadways at no charge.

(c) Underground Industrial Developments (raw land)

- Upon completion of the underground servicing of an industrial area, EDTI will provide a rebate determined as 80% of the total installed cost of the underground distribution facilities installed to service raw industrial land. This cost will be calculated by EDTI based on EDTI's costs, as determined and published by EDTI from time to time, for the types of cables and switching cubicles installed, and for such activities as trenching and terminations.



---

## 2. Eligibility for Investment

- (a) The following Facilities are eligible for investment:
- distribution three-phase and single-phase extensions;
  - transformers (or a share of a transformer, if the transformer is shared by more than one Customer e.g. rural acreages);
  - standby feeder where required by EDTI;
  - primary cable to EPCOR Transformer on property (excluding Multi-Family Sites)
- (b) The following Facilities are not eligible for investment:
- transformer pad and civil works on private property;
  - standby feeders not required by EDTI;
  - secondary underground services in aerial distribution areas.